

CLAIMS

1. A digital pulse-width-modulation (PWM) generator comprising:
 - an n bit digital magnitude comparator having first and second n bit inputs and an output indicative of the relative values of the signals applied at the first and second inputs;
 - a first n bit digital up/down counter having a count direction input coupled to receive a sign bit of a digital unary input signal, an n bit parallel binary count output connected to the first n bit input of the magnitude comparator, and a clock input;
 - a second n bit counter having a clock input coupled to receive a constant rate clock signal and an n bit parallel binary count output connected to the second n bit input of the magnitude comparator;
 - an AND gate having a first input coupled to receive the constant rate clock signal in frequency divided form and a second input coupled to receive a magnitude portion of the digital unary input signal, and further having an output connected to the clock input of the first counter; and
 - wherein the comparator continually generates an output signal indicative of the relative magnitudes of the counts of the first and second counters, whereby said output signal is a PWM output signal with an average value representing a ramp voltage having a slope determined by magnitude portion of the digital unary input signal with a direction of a slope of the output signal being determined by the polarity of the sign bit.
2. A digital pulse-width-modulation (PWM) generator as claimed in claim 1, wherein the n bit parallel binary count output of the first n bit digital up/down counter is connected to the first n bit input of the magnitude comparator with a least significant bit (LSB) of the output connected to a LSB of the first input of the comparator and thereafter in bit significance sequence, and the n bit parallel binary count output of the second n bit counter is connected to the second n bit input of the magnitude comparator with a LSB of the output connected to a LSB of the second input of the comparator and thereafter in bit significance sequence.
3. A digital pulse-width-modulation (PWM) generator as claimed in claim 1 wherein the n bit parallel binary count output of the second n bit digital up/down counter is connected to the second n bit input of the magnitude comparator with a most significant bit (MSB) of the output connected to a LSB of the second input of the comparator and thereafter in reverse bit significance sequence, and the n bit parallel binary count output of the first n bit counter is connected to the first n bit input of the magnitude comparator with a LSB of the output connected to a LSB of the first input of the comparator and thereafter in bit significance sequence.
4. A digital pulse width modulation generator comprising an up/down digital counter, a digital magnitude comparator, and a second digital counter, wherein the magnitude comparator compares the relative sizes of the counts in the two counters connected to the magnitude comparator in the conventional sense with least significant bit outputs connected to least significant bit inputs of the comparator and

1990 1991 1992

5. A digital pulse width modulator as claimed in claim 4 except that the outputs of the second counter are connected to one of the input ports of the magnitude comparator in bit-reversed order that is in the reverse of the conventional ordering of bits and in particular with the least significant bit output of the counter connected to the most significant bit input of the comparator and vice versa, such that the pulse width modulated output from the comparator now makes many more transitions per total count cycle of the second counter whilst still maintaining the required average mark:space ratio, thus easing the usually required low pass filtering of the pulse width modulated output